# ACN | DigitalTalk® EXPRESS
*for business*

## HOW TO CHANGE LINE TO DEVICE PAIRING FOR YOUR
### *Panasonic KX-TGP600* BASE STATION

When replacing one handset/desktop phone with another, both need to have their individual registration canceled/deleted in the Base Station. The steps below must be performed for each handset/desk phone involved in the replacement.

## REMOVE LINE FROM ASSOCIATED DEVICE:

1. From a handset/desktop phone that is not being replaced, press the **MENU** key then select the **System Settings** key and press **OK.**

2. Select **System Settings** again and press **OK**.

3. Select **Cancel Register** and press **OK.**

4. Select the telephone number that is associated with the handset/desktop phone you would like to replace and press **OK.**

5. **"Executing"** will be displayed, followed by **"Deleted."** The handset/desktop phone replaced will say **"Register Unit."**

6. Repeat steps 1-5 for each handset/desktop phone to be replaced.

## ADD LINE TO ASSOCIATED DEVICE:

1. Handset/desktop phone will register, in order, to the available telephone numbers listed in System Settings – System Settings – Register H/S.

2. Press and hold the handset locator button (on the right side of the base station) for about 4 seconds until the Status LED flashes red.

3. On the desired handset/desktop phone press and hold **OK** until **"Please Wait"** is displayed.

4. This handset/desktop phone will be paired with the first telephone number made available in steps 1-5 above. Registration is complete on the handset/desktop phone when **"Registered"** is displayed.

5. Repeat steps 1-4 until all handset/desktop phone are paired with a telephone number.

**Panasonic KX-TPA65**
**Desktop Phone**



**Panasonic KX-TGP600**
**Wireless Base Station**

**Panasonic KX-TPA60**
**Cordless Handset**